

## Penn Power Eligibility List File Format

customer number(20)  
 meter number (9)  
 name1(36)  
 name2(36)  
 servaddr1(36)  
 servcty(36)  
 servst(3)  
 servzip(10)  
 billing\_addr1(36)  
 billing\_addr2(36)  
 billing\_city(36)  
 billing\_st(3)  
 billing\_zip(10)  
 budget indicator(1)  
 meter\_read\_cyc(3)  
 meter\_type(11)  
 profile\_grp(11)  
 interval\_mtr\_flg(2)  
 rate\_catg(11)  
 loss\_factor(3)

24 months historical usage

meter read date(9)

billdays(6)

consumption(40)

If the account is time of day, on-peak kWh will be displayed followed by an underscore and the off-peak consumption. Example: 500\_750

demand(40)

If the account is time of day, on-peak kW will be displayed followed by an underscore and the off-peak demand. Example: 18.1\_7.5

capacity\_pls(20)

polr\_ind(1)

trans\_pls(20)

voltage\_level(2)

contract\_acct(12)

phone\_number(30)

capacity\_pls\_future(20)

net\_metering\_ind(1)

<b>Penn Power Loss Factor Key</b>		
<b>Loss Class ID</b>	<b>Voltage Levels</b>	<b>Loss Factor</b>
<b>0</b>	01, 02, 03, 04, 05, 06, 07, 08, 29, 30, 31, 32	1.0896
<b>2</b>	21, 22, 46, 47, 48	1.02886
<b>3</b>	23, 24, 49, 50, 51	1.02786
<b>4</b>	25, 26, 27, 52, 53, 54, 55, 56	1.01486
<b>5</b>	09, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 28, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45	1.05786

Penn Power Eligibility List File Format

<b>Voltage Key</b>	
1	120 volt single phase
2	120/240 volt single phase
3	120/208Y single phase(network)
4	240/480V single phase (DOT)
5	208Y/120 Volt 3 phase
6	120/240 Volt Delta 3 phase
7	480Y/277 Volt 3 phase
8	240/480 Volt Delta 3 phase
9	2400 Volt single phase
10	4800 Volt single phase
11	7200 Volt single phase
12	7620 Volt single phase
13	2400 Volt Delta 3 phase
14	4160Y/2400 Volt 3 phase
15	4800 Volt Delta 3 phase
16	7200 Volt 3 phase
17	8320Y/4800 Volt 3 phase
18	12470Y/7200 Volt 3 phase
19	13200Y/7620 Volt 3 phase
20	22860Y/13200 Volt 3 phase
21	34500Y/19900 Volt 3 phase
22	34500 Delta Volt 3 phase
23	69000 Delta Volt 3 phase
24	115000 Volt 3 phase
25	138000 Volt 3 phase
26	230000 Volt 3 phase
27	345000 volt 3 phase
28	Primary, voltage unknown
29	Secondary, voltage unknown
30	240 Volt Delta
31	480 Volt Delta
32	120/208 Volt Delta 4W
33	1440Y/2494 Volt
34	2400Y/4160 Volt
35	4200Y/7280 Volt
36	4340 Volt Delta
37	8400Y/14560 Volt
38	9600 Volt Delta
39	11500 Volt Delta
40	12000 Volt Delta
41	12000Y/20780 Volt
42	13200 Volt Delta
43	13800 Volt Uni-Grd Y

## Penn Power Eligibility List File Format

<b>44</b>	14400 Volt Delta
<b>45</b>	14400Y/24000 Volt
<b>46</b>	23000 Volt Delta
<b>47</b>	27600 Volt Delta
<b>48</b>	34500 Volt Uni-Grd Y
<b>49</b>	40250Y/69000 Volt
<b>50</b>	46000 Volt Delta
<b>51</b>	115000 Volt Delta
<b>52</b>	138000 Volt Delta
<b>53</b>	230000 Volt Delta
<b>54</b>	240000 Volt Delta
<b>55</b>	345000 Volt Delta
<b>56</b>	500000 Volt Delta
<b>57</b>	25000 Volt 3 phase
<b>58</b>	Subtransmission, voltage unknown
<b>59</b>	Transmission, voltage unknown