

Ohio Operating Company Layout

Record DATA:

Company_No pic X(7)
 Meter_No pic X(10)
 Name1 pic x(35)
 Name2 pic x(35)
 Srvc_Addr1 pic x(35)
 Srvc_City pic x(35)
 SrvcSt pic x(2)
 Srvc_Zip pic x(9)
 Bllng_Addr1 pic x(35)
 Bllng_Addr2 pic x(35)
 Bllng_City pic x(35)
 Bllng_St pic x(2)
 Bllng_Zip pic x(9)
 Budget_Pip_Flag pic x(1)
 Meter_Read_Cyc pic x(2)
 Meter_Type pic x(10)
 Profile_Grp pic x(10)
 Interval_Mtr_Flg pic x(1)
 Rate_Catg pic x(10)
 Loss_Factor pic x(1) *See Ohio Loss Factor Key Below*
 EDR_Flag pic x(1) *See EDR (Economic Development Rider) Key Below*
 12 months of:
 Lrddtes pic X(8)
 Bilclds pic x(1)
 Conhsts pic X(10)
 Demext_Conv pic x(11)
 capacity_pls(20)
 trans_pls(20)
 capacity_pls_future(20)
 net_metering_ind(1)

Rider EDR (Economic Development Rider) Key	
1	Account was receiving water heating discount
2	Account was receiving electric space heating or all electric discount
3	Account was being billed using a demand reading
4	School
5	Mercantile

Ohio Operating Company Layout

Ohio Loss Factor Key		
Loss Class ID	Voltage Levels	Loss Factor
0	01, 02, 03, 04, 05, 06, 07, 08, 29, 30, 31, 32	1.09486
2	21, 22, 46, 47, 48	1.02886
3	23, 24, 49, 50, 51	1.02786
4	25, 26, 27, 52, 53, 54, 55, 56	1.01486
5	09, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 28, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45	1.05786

Voltage Key	
1	120 volt single phase
2	120/240 volt single phase
3	120/208Y single phase(network)
4	240/480V single phase (DOT)
5	208Y/120 Volt 3 phase
6	120/240 Volt Delta 3 phase
7	480Y/277 Volt 3 phase
8	240/480 Volt Delta 3 phase
9	2400 Volt single phase
10	4800 Volt single phase
11	7200 Volt single phase
12	7620 Volt single phase
13	2400 Volt Delta 3 phase
14	4160Y/2400 Volt 3 phase
15	4800 Volt Delta 3 phase
16	7200 Volt 3 phase
17	8320Y/4800 Volt 3 phase
18	12470Y/7200 Volt 3 phase
19	13200Y/7620 Volt 3 phase
20	22860Y/13200 Volt 3 phase
21	34500Y/19900 Volt 3 phase
22	34500 Delta Volt 3 phase
23	69000 Delta Volt 3 phase
24	115000 Volt 3 phase
25	138000 Volt 3 phase
26	230000 Volt 3 phase
27	345000 volt 3 phase
28	Primary, voltage unknown
29	Secondary, voltage unknown
30	240 Volt Delta
31	480 Volt Delta
32	120/208 Volt Delta 4W
33	1440Y/2494 Volt

Ohio Operating Company Layout

34	2400Y/4160 Volt
35	4200Y/7280 Volt
36	4340 Volt Delta
37	8400Y/14560 Volt
38	9600 Volt Delta
39	11500 Volt Delta
40	12000 Volt Delta
41	12000Y/20780 Volt
42	13200 Volt Delta
43	13800 Volt Uni-Grd Y
44	14400 Volt Delta
45	14400Y/24000 Volt
46	23000 Volt Delta
47	27600 Volt Delta
48	34500 Volt Uni-Grd Y
49	40250Y/69000 Volt
50	46000 Volt Delta
51	115000 Volt Delta
52	138000 Volt Delta
53	230000 Volt Delta
54	240000 Volt Delta
55	345000 Volt Delta
56	500000 Volt Delta
57	25000 Volt 3 phase
58	Subtransmission, voltage unknown
59	Transmission, voltage unknown